



BLUETOOTH WIRELESS SPEAKER



USER MANUAL

SMPS-620

PLEASE READ THIS USER MANUAL COMPLETELY
BEFORE OPERATING THIS UNIT AND RETAIN THIS
BOOKLET FOR FUTURE REFERENCE.

DEAR JENSEN® CUSTOMER

Selecting fine audio equipment such as the unit you've just purchased is only the start of your musical enjoyment. Now it's time to consider how you can maximize the fun and excitement your equipment offers. This manufacturer and the Electronic Industries Association's Consumer Electronics Group want you to get the most out of your equipment by playing it at a safe level. One that lets the sound come through loud and clear without annoying blaring or distortion and, most importantly, without affecting your sensitive hearing. Sound can be deceiving. Over time your hearing "comfort level" adapts to higher volumes of sound. So what sounds "normal" can actually be loud and harmful to your hearing. Guard against this by setting your equipment at a safe level BEFORE your hearing adapts.

To establish a safe level:

- Start your volume control at a low setting.
- Slowly increase the sound until you can hear it comfortably and clearly, and without distortion.

Once you have established a comfortable sound level:

- Set the dial and leave it there.

Taking a minute to do this now will help to prevent hearing damage or loss in the future. After all, we want you listening for a lifetime.

We Want You Listening For a Lifetime

Used wisely, your new sound equipment will provide a lifetime of fun and enjoyment. Since hearing damage from loud noise is often undetectable until it is too late, this manufacturer and the Electronic Industries Association's Consumer Electronics Group recommend you avoid prolonged exposure to excessive noise.



Customer's Record:

The serial number of this product is found on its back cover. You should note the serial number of this unit in the space provided as a permanent record of your purchase to aid in identification in the event of theft or loss.

Model Number: SMPS-620

Serial Number: _____

COMPLIANCE WITH FCC REGULATIONS

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE : This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

CAUTION: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

PROTECT YOUR FURNITURE

This model is equipped with non-skid rubber 'feet' to prevent the product from moving when you operate the controls. These 'feet' are made from non-migrating rubber material specially formulated to avoid leaving any marks or stains on your furniture. However certain types of oil based furniture polishes, wood preservatives, or cleaning sprays may cause the rubber 'feet' to soften, and leave marks or a rubber residue on the furniture. To prevent any damage to your furniture we strongly recommend that you purchase small self-adhesive felt pads, available at hardware stores and home improvement centers everywhere, and apply these pads to the bottom of the rubber 'feet' before you place the product on fine wooden furniture.

PRODUCT FEATURES

The SMPS-620 is a Bluetooth portable speaker with the following features:

- Wireless playback of music from your Bluetooth enabled cell phone via the Bluetooth connection
- Up to 33 feet (10 meters) operating range


GETTING STARTED

ACCESSORIES INCLUDED

Carefully remove the unit and all the accessories from the display carton. Please verify that you have all the following accessories before recycling the gift box.

- User manual
- USB cable

LOCATION OF CONTROLS



1. POWER/CHARGING/ BLUETOOTH STATUS INDICATOR (RED / BLUE)
2. POWER/ANSWER BUTTON
3. BUILT IN MICROPHONE
4. RESET BUTTON
5. CHARGING JACK (mini USB jack)

CHARGING INSTRUCTIONS

This unit operates on a built-in Li-ion battery that can be recharged either using the USB port on your computer or from a USB power adaptor (not included) with a rated output of DC 5V, 500mA and up.

Note: The mini USB CHARGING JACK located on this unit is only designed for charging the built-in Li-ion battery.

CHARGING THE BATTERY FOR FIRST TIME

- 1.) Charge the built-in Li-ion battery a minimum of 2 hours prior to first use. Plug the unit into the USB port on your computer or into a USB power adaptor (not included) using the included USB cable.
- 2.) The LED indicator will turn red while charging and turn blue when the unit is fully charged. Unplug the USB cable from the power source once the battery is fully charged.

RECHARGING THE INTERNAL BATTERY

After prolonged use, the internal battery will become weak and the operation may become intermittent. When the internal battery charge is very low, the Indicator LED will flash red and a melody will play alerting you to recharge the internal battery as soon as possible.

Plug the speaker into a USB port on your computer or into a DC 5V, 500mA and up USB power adaptor (not included) using the included USB cable. Disconnect the USB cable from the speaker as soon as it is fully charged.

Charging in Power ON mode

- The **Indicator LED** is **RED** while charging.
- The **Indicator LED** will change from **RED** to **BLUE** when the battery is fully charged.

- Note:**
1. Charging time will vary if you are listening to music while charging the internal battery. We recommend you switch off the speaker power during the charging process.
 2. To prolong the life of a rechargeable battery, it is recommended to completely discharge it before fully charging it again.
 3. Rechargeable batteries need to be cycled for maximum performance and longer battery life. If you don't use the player that often, be sure to recharge the battery at least once a month in order to keep the internal battery working properly.

Charging in Unit Power OFF mode

- The **Indicator LED** is **RED** while charging.
- The **Indicator LED** will change from **RED** to **BLUE** when the battery is fully charged.



Battery Note and Care

- Do not burn or bury batteries.
- Do not puncture or crush.
- Do not disassemble.
- Li-ion batteries must be recycled. Do not dispose of in the trash.
- Use only chargers rated for Li-ion cells. Be sure the charger's voltage and current settings are correct for the battery pack being charged.
- Charge batteries on a fireproof surface and away from flammable items or liquids.
- Batteries should NEVER be left unattended while charging. Only adults should charge the batteries.
- Follow the manufacturer's instructions for charging the product and do not charge longer than recommended. Unplug the charger when the battery is charged or not in use.

Note: The speaker is not magnetically shielded and may cause color distortion on the screen of some TVs or video monitors. To avoid this, you may need to move the unit further away from the TV or monitor if an unnatural color shifts or image distortion occurs.

TURNING THE SMPS-620 POWER ON/OFF

1. In standby mode, press and hold the **POWER/ANSWER** button for 2-3 seconds until a beep sound is heard to turn the unit ON, the **Indicator LED** will flash blue 3 times.
2. To turn the unit OFF, press and hold the **POWER/ANSWER** button for 4-5 seconds until a beep sound is heard and the **Indicator LED** flashes red for about 0,5 second. Don't forget to turn off the Bluetooth feature on your cell phone.

SPEAKER OPERATIONS

PAIRING (LINKING) A BLUETOOTH ENABLED CELL PHONE OR OTHER BLUETOOTH ENABLED DEVICE TO THE SMPS-620

1. If the SMPS-620 has never been paired with a Bluetooth device before. You need to follow the

pairing instructions below to link the SMPS-620 with your Bluetooth device.

- In standby mode, press and hold the **POWER/ANSWER** button for 5-6 seconds until a beep sound is heard, the Indicator LED will alternately flash blue and red. The speaker is ready to pair (link) with your Bluetooth device.
 - Turn on the Bluetooth function of your cell phone and enable the search or scan function to find the SMPS-620.
 - Select "SMPS-620" from the device list when it appears on your device screen. If required, enter the pass code "0000" to pair (link) the SMPS-620 with your cell phone or Bluetooth device.
2. After turning on the SMPS-620, the unit will search for the last paired device. The **POWER/CHARGING/BLUETOOTH STATUS INDICATOR** will flash rapidly in blue. If the unit finds the paired Bluetooth device, a beep is heard and the **POWER/CHARGING/ BLUETOOTH STATUS INDICATOR** will begin flashing at a slower rate.

Remarks:

- Fast flashing is when the LED lights up 3 times every second.
 - Slow flashing is when the LED lights up 1 time every 8 seconds.
3. After successfully pairing (linking), you can begin playing music from your Bluetooth device wirelessly to the speaker.
 4. Press the Volume Up(+) / Down(-) button on your Bluetooth device to adjust to the desired volume level.

Notes:

1. Refer to manual of your cell phones, tablet, PC, computer or other Bluetooth enabled device for Bluetooth operation, since it may vary from model to model.
2. Your Bluetooth enabled device will not play the music through the speaker, even if connected (linked), if the device does not support A2DP profile.
3. If you are pairing (linking) your computer to the SMPS-620 using Bluetooth, you may need to set the speaker as your computer's default sound device.
4. If the SMPS-620 is left idle for about 5 minutes without linking to any Bluetooth enabled device, it will automatically turn off to save battery power.

Using the SMPS-620 as a Handsfree Bluetooth Speakerphone

1. Link your cell phone to the SMPS-620 via Bluetooth as described above.
2. When receiving an incoming call on your cell phone, tap the **POWER/ANSWER** button on the speaker to switch the incoming call from cell phone to the SMPS-620 speaker. A short beep sound will be heard confirming the call was answered. Complete your call using the built-in microphone and speaker on the SMPS-620.
3. Adjust the volume control of your cell phone to obtain the desired sound level.
4. To end the call, just tap the **POWER/ANSWER** button again on the SMPS-620. A short beep sound will be heard and the call will end. If you were playing music from your cell phone to the SMPS-620 speaker before answering the call, the music will automatically resume playing when you hang up.
5. To ignore an incoming call, simply press and hold the **POWER/ANSWER** button on the speaker for about 2 seconds, a beep sound will be heard and the call will be ignored.

Redialing the last number with the speaker

The speaker will automatically redial the last number you dialed by tapping the speaker **POWER/ANSWER** button twice.

Note: This feature is phone dependent.

Hang up with the SMPS-620

A quick press on the **POWER/ANSWER** button will end the call in progress. A short beep tone will be heard from the speaker confirming the call has ended.

Re-linking to the cell phone

If your cell phone is already paired (linked) with the speaker, but became unlinked even with both Bluetooth devices turned on. You can re-link them by:

1. Turning off the speaker and then turning it on again to re-link your cell phone. The **POWER/CHARGING/ BLUETOOTH STATUS INDICATOR** will flash three times with two short beeps and then flash rapidly around 2 seconds if the speaker and your cell phone have been re-linked successfully.
2. You can also re-link the speaker by using Bluetooth operation of your cell phone. Please refer to operation manual of your cell phone for more information.

RESETTING

If the speaker does not respond or has erratic or intermittent operation, it may have been subjected to an electrostatic discharge(ESD) or a power surge that triggered the internal circuitry to shut down automatically. If this occurs, press the reset button on the bottom of the speaker to reset it.

CARE AND MAINTENANCE

1. Avoid operating your unit under direct sunlight or in hot, humid or dusty places.
2. Keep your unit away from heating appliances and sources of electrical noise such as fluorescent lamps or motors.

CLEANING THE UNIT

- To prevent fire or shock hazard, disconnect your unit from the USB port of power source when cleaning.
- The finish on the unit may be cleaned with a dust cloth and cared for as other furniture. Use caution when cleaning and wiping the plastic parts.
- If the cabinet becomes dusty wipe it with a soft dry dust cloth. Do not use any wax or polish sprays on the cabinet.
- If the front panel becomes dirty or smudged with fingerprints it may be cleaned with a soft cloth slightly dampened with a mild soap and water solution. Never use abrasive cloths or polishes as these will damage the finish of your unit.

CAUTION: Never allow any water or other liquids to get inside the unit while cleaning.

TROUBLESHOOTING GUIDE

Symptom	Possible Problem	Solution
No Charging	The USB power adaptor (not included) is not plugged into a wall outlet or the USB cable (included) is not plugged into the mini USB jack on the bottom of the SMPS-620.	Plug the USB power adaptor (not included) into a wall outlet and plug the USB cable (included) into the mini USB jack on the the SMPS-620.
	Wall outlet is not functioning.	Plug another device into the same outlet to confirm the outlet is working.
	Computer USB port is not functioning.	Make sure your computer power is turned on and try another USB port.
No Sound	The SMPS-620 battery is dead.	Recharge the SMPS-620 battery.
	The SMPS-620 is not linked with the cell phone.	Go through "Speaker Operations" process to link the speaker.
	The SMPS-620 placement is out of range.	Relocate the SMPS-620 within Bluetooth operating range (30 feet).
	Volume set too low.	Increase the volume of your device.
Sound is distorted.	Volume level is set too high.	Decrease the volume of your device.
	Sound source is distorted.	If the source sound file is of poor quality, distortion and noise are easily noticed with high-power speakers. Try a different audio source such as a music CD.
Unit gets warm after extended play at high volume.	This is normal.	Turn the unit off for a period of time or lower the volume.

SPECIFICATIONS

Power Requirement

Main unit

Built-in DC 3.7V 420mAh rechargeable Li-ion Battery



At Spectra, environmental and social responsibility is a core value of our business. We are dedicated to continuous implementation of responsible initiatives with an aim to conserve and maintain the environment through responsible recycling.

Please visit us at <http://www.spectraintl.com/green.htm> for more information on Spectra's green initiatives or to find a recycler in your area.

Bluetooth® is a registered trademark of Bluetooth SIG, Inc.

90 DAY LIMITED WARRANTY AND SERVICE VALID IN THE U.S.A. ONLY

SPECTRA MERCHANDISING INTERNATIONAL, INC. warrants this unit to be free from defective materials or factory workmanship for a period of 90 days from the date of original customer purchase and provided the product is utilized within the U.S.A. This warranty is not assignable or transferable. Our obligation under this warranty is the repair or replacement of the defective unit or any part thereof, except batteries, when it is returned to the SPECTRA Service Department, accompanied by proof of the date of original consumer purchase, such as a duplicate copy of a sales receipt.

You must pay all shipping charges required to ship the product to SPECTRA for warranty service. If the product is repaired or replaced under warranty, the return charges will be at SPECTRA's expense. There are no other express warranties other than those stated herein.

This warranty is valid only in accordance with the conditions set forth below:

1. The warranty applies to the SPECTRA product only while:
 - a. It remains in the possession of the original purchaser and proof of purchase is demonstrated.
 - b. It has not been subjected to accident, misuse, abuse, improper service, usage outside the descriptions and warnings covered within the user manual or non-SPECTRA approved modifications.
 - c. Claims are made within the warranty period.
2. This warranty does not cover damage or equipment failure caused by electrical wiring not in compliance with electrical codes or SPECTRA user manual specifications, or failure to provide reasonable care and necessary maintenance as outlined in the user manual.
3. Warranty of all SPECTRA products applies to residential use only and is void when products are used in a nonresidential environment or installed outside the United States.

This warranty gives you specific legal rights, and you may also have other rights which vary from state to state. TO OBTAIN SERVICE please remove all batteries (if any) and pack the unit carefully and send it freight prepaid to SPECTRA at the address shown below. IF THE UNIT IS RETURNED WITHIN THE WARRANTY PERIOD shown above, please include a proof of purchase (dated cash register receipt) so that we may establish your eligibility for warranty service and repair of the unit without cost. Also include a note with a description explaining how the unit is defective. A customer service representative may need to contact you regarding the status of your repair, so please include your name, address, phone number and email address to expedite the process.

IF THE UNIT IS OUTSIDE THE WARRANTY PERIOD, please include a check for \$20.00 to cover the cost of repair, handling and return postage. All out of warranty returns must be sent prepaid.

It is recommended that you contact SPECTRA first at 1-800-777-5331 or by email at custserv@spectraintl.com for updated information on the unit requiring service. In some cases the model you have may be discontinued, and SPECTRA reserves the right to offer alternative options for repair or replacement.

SPECTRA MERCHANDISING INTERNATIONAL, INC.
4230 North Normandy Avenue,
Chicago, IL 60634, USA.
1-800-777-5331

To register your product, visit the link on the website below to enter your information.

<http://www.spectraintl.com/wform.htm>